

## High bay specification sheet



# Area Bay 24,000lm

150W High bay luminaire (Replaces 250W or 4X49W T5)

## Features

|                        |  |
|------------------------|--|
| IK Rating              | IK10                                       |
| IP Rating              | IP65                                       |
| CSP Switchable         | Single CCT                                 |
| Sensor Option          | PIR, Microwave & Daylight with accessories |
| Dimmable Option        | Yes (0-10V, PWM and DALI-2)                |
| LED Lifetime           | L80 54,000h                                |
| Colour Rendering Index | CRI>80                                     |
| Colour Consistency     | SDCM5                                      |
| Emergency Option       | Yes, Manual-Test                           |

## Installation information

|                           |   |
|---------------------------|---|
| Install Connector Type    | Flying lead                                   |
| Inrush Current            | 130A 0.63ms                                   |
| Construction Material     | ADC12 ALU alloy, PC front lens, SS304 Eyelet. |
| Weight                    | 2.28kg  |
| Ambient Temperature Range | -40°C - 50°C                                  |
| UK Building Regulations   | Part P  |
| Electric Class (1, 2, 3)  | 1   |

## Photometrics @ 25°C

| Product code | Finish             | Feature I | W    | Colour | Beam | lm    | lm/W | EM  |
|--------------|--------------------|-----------|------|--------|------|-------|------|-----|
| HBA2V        | Matt black RAL9017 | Standard  | 150W | 4000K  | 110° | 24000 | 160  | -   |
| HBA2VEM      | Matt black RAL9017 | Emergency | 150W | 4000K  | 110° | 24000 | 160  | 650 |
| HBA2D        | Matt black RAL9017 | DALI-2    | 150W | 4000K  | 110° | 24000 | 160  | -   |

Energy rating is a reflection of the LED light source.

## Wiring information

|                         |  |
|-------------------------|--|
| Cable / Flying Lead     | 1.5m H05RN-F 3x1.0mm <sup>2</sup> Ø7mm |
| Type of Wiring Required | Parallel                               |

## Accessories

|         |   |                 |
|---------|---|-----------------|
| HBPIRDL | Area Bay PIR + Daylight Harvest Sensor  | Sold Separately |
| HBPIR   | Area Bay PIR/Daylight Sensor            | Sold Separately |
| HBMWS   | Area Bay Microwave/Daylight Sensor      | Sold Separately |
| HBDLS   | Area Bay Daylight Sensor                | Sold Separately |
| HBBRA   | HB Bracket Mount for Standard Luminaire | Sold Separately |



collingwood

01604 495 151  
collingwoodlighting.com

- collingwoodled
- /collingwoodlighting
- collingwoodlighting

## Guarantee

5 years, 2 years on emergency battery

## Features & benefits

High efficacy of 160lm/W

Very light weight for easy installation

Emergency option available

High performance dedicated lens for each LED provides efficient optical control

Choice of PIR, microwave, daylight and wireless control options saves energy and takes just seconds to fit, just plug-in to the centre of the high bay

Compact and lightweight, our product can be held in one hand and installed by a single person

Quick access to LiFePO4 battery compartment for simple replacement

Removeable driver for easy maintenance

Impact and corrosion resistant aluminium housing which is 100% recyclable

Light source energy efficiency:



Beam angle: 110°

