



PIR Sensor

Passive infra-red motion sensor with daylight threshold switch

Features

IP Rating	IP65
-----------	------

Installation information

Install Connector Type	Zhaga Book 18
UK Bathroom Zone	N/A
Weight	0.03

USE WITH

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------

PRODUCT CODES

	Colour / Finish	Description
HBPIR	Matt black RAL9017	Passive infra-red (PIR) motion sensor with daylight threshold switch



collingwood

01604 495 151
collingwoodlighting.com

- collingwoodled
- /collingwoodlighting
- collingwoodlighting

Guarantee

5 years

Features & benefits

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Typical installation height 8-13m

Hold time Default is 5 seconds - Options 30s/1min/3min/5min/10min/20min/30min

Stand-by dimming level: Default is 10% Options - 20%/30%/50%

Stand-by period: Default is 0 seconds - Options - 10s/30s/1min/5min/10min/30min

Daylight threshold: Default is 'disable' - Options - 2Lux/10Lux/30Lux/50Lux/120Lux/200Lux/250Lux/300Lux/350Lux/400Lux

Use remote controller HBREM to commission