



LEDEP11

Emergency converter for H2 and H4 Pro, self-test, maintained.

INSTALLATION INFORMATION

Install Connector Type	Mains: Push-fit terminals 0.5 - 2.5mm² DC: Plug & Play connectors
Insulation Coverable	No
Double Insulation	Yes
Cut Out Size	18 (status LED) 7 (test button)
Inrush Current	1.5A 0.6ms
Construction Material	Polycarbonate
Weight	294g
Ambient Temperature Range	0°C - 50°C
SELV	SELV
Electric Class (1, 2, 3)	2

Wiring information

Cable / Flying Lead	Plug & Play connectors
Type of Wiring Required	Parallel

Accessories

No accessories required

PRODUCT CODES

	Colour / Finish	Description	Characteristic 1	Characteristic 2
LEDEP11	Matt white	Emergency converter for H2 and H4 Pro, Self-test, maintained	LiFePO4 battery	6.4V 1500mAh



collingwood

01604 495 151
collingwoodlighting.com

- collingwoodled
- /collingwoodlighting
- collingwoodlighting

Guarantee

3 year extended guarantee

Features & benefits

- Self-test device, simplifying the inspections
- LiFePO4, provides long operational life
- A minimum of 3 hours of emergency lighting
- Built-in protection: - open circuit - over charging - over discharging - over temperature
- Dual colour Green / Red LED status indicator
- Supplied with a test button, whereby a battery duration test can be carried out at anytime
- Synchronizes an automatic battery duration test every 6 months
- Compatible with our H2 and H4 Pro colour and lumen switchable downlights
- IP20

