

BMA Male Connector for RG405 or .086" Cable | 2 Holes Flange | DC-18GHz

P/N: FR2-JBMA-JFB2



Product Configuration

Body Style	Straight
Connector Series	BMA
Connector Polarity	Standard
Connector Gender	Male
Termination Type	Coax
Connector Impedance (Ohm)	50
Mount Method	2 Hole Flange

Electrical Specifications

Frequency	DC - 18GHz
VSWR / Return Loss	1.30 to 18GHz
Insertion Loss	≤ 0.10 x Sqrt.(f_GHz)

Mechanical Data

Min. Mating Cycles	≥500
Body Material	Brass
Body Plating	Gold

Environmental Specifications

RoHS Compliant	Yes
Operating Temperature Range	-55 °C to +165 °C
MIL/STD	N/A