# EU 1G DIMMER / 250W MULTIPOINT LED / RETRACTIVE

**ACTION: DIMMER SWITCH**

**KNURL: CROSS**

**RANGE: DIMMER SWITCHES**

A solid metal dimmer switch with our classic diamond-cut knurling. The switch is finished with a solid metal plate and our signature coin screws. Available in five different finishes, they can be used in combination with our matching toggle switches, sockets and USB outlets.









## SPECIFICATIONS

Solid metal switch plate with one multipoint dimmer, in our signature white, steel, brass, smoked bronze and black finishes.

Module: CDM-142038
Style: Push On / Off Rotary Dimmer
Switching: Multi-location dimming using retractive switches
Input: 240VAC
Dimming Type: Auto-detect trailing edge and leading edge (with manual override)
Load: 10-350W - Incandescent / 3-250W - LED
Certified for use in UK, Europe and Russia: UKCA / CE / EAC
Certification: EN 60669-2-1

For use with retractive switches on retractive dimming circuits, to control dimming from multiple locations.
Not compatible with standard wiring and standard 1-way, 2-way and 3-way wiring accessories.
Not suitable for motors, fans or any other type of large inductive load.

The dimmer switch incorporates a soft-start feature, which may result in a 1–2 second delay before full illumination to reduce inrush current and extend lamp life.
This module is custom to Buster + Punch and works only with our Cross and Linear knurled dimmer knobs.
note: rotary action includes a soft, audible ticking feedback during adjustment.

Compatible with European standard electricity backboxes. Backbox must be flush mounted.
For indoor use only.
This piece features a 6.5mm shadow gap when installed.

## FINISH & SKU NUMBERS

| sku: | finish: | size: |
|---|---|---|
| CDR-021975 | black | 1G |
| CDR-051976 | brass | 1G |
| CDR-091978 | smoked bronze | 1G |
| CDR-141974 | white | 1G |

## INCLUDED

1 x Complete Dimmer Switch Assembly

## PLEASE NOTE

DISCLAIMER: Always consult a trade professional when installing this product. Buster + Punch is not responsible for the usage or feasibility of installation requirements. This product is not suitable for damp or wet environments.

## CARE INSTRUCTIONS

Wipe with a dry lint free cloth with no loose hairs, avoid using any chemicals. Please note that finishes may age naturally with time and regular use.