



# CASAMBI WIRELESS BOLT-ON SENSOR

PIR+Daylight M20 Conduit Entry Sensor for use up to 7m

## FEATURES

<b>IP rating</b>	IP65
<b>Dimmable Option</b>	Yes (0-10V)

## INSTALLATION INFORMATION

<b>Input</b>	220-240V AC
<b>Maximum Ambient Temperature</b>	-20°C - 60°C
<b>Electric Class (1, 2, 3)</b>	II
<b>Install Connector Type</b>	Flying lead
<b>UK Building Regulations</b>	Part P & L
<b>Dimmer Type</b>	App controlled

## PHOTOMETRICS @ 25°C

<b>Product code</b>	<b>Finish</b>
CASBOLT7W	White

## ACCESSORIES

<b>Use with Borealis Versa</b>	Requires 0-10V driver	Sold Separately
<b>Use with Caiman Versa</b>	Requires 0-10V driver	Sold Separately
<b>Use with Uniform Versa</b>	Requires 0-10V driver	Sold Separately
<b>Use with Rack Bay</b>	Requires 0-10V driver	Sold Separately



Casambi Ready



Bluetooth Mesh



Wireless Control

## WARRANTY

Warranty

5 years

## FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation – No extra control wiring, gateways, or routers needed

Fast Commissioning – Configure and adjust settings via the Casambi App

10-16m cone detection pattern when installed at 7m

