

All-in-one Driver for  
RGBW/RGB Systems

Selectable Voltage by dips  
(8-43V)

Receives RF signal

## WARRANTY

Warranty

5 years

## FEATURES & BENEFITS

4 channel output Constant Current (RGBW)

Multiple control inputs

Works with 350mA to 1500mA & 8-43V products

Power repeaters (PR3011) are required for RF installations with multiple zones that want to colour cycle. Requires driver.

# CCDRV75RF

75W RF Driver

## INSTALLATION INFORMATION

Input	220-240V AC
Maximum Ambient Temperature	-25°C - 40°C
Inrush Current	COLD START Max. 2A @ 230VAC
UK Bathroom Zone	2
SELV	Yes
Electric Class (1, 2, 3)	II
Power Factor	0.9

## Electrical Characteristics

Driver Rated Wattage	Driver Input Voltage	Drive Current	Driver Output Voltage	Power Factor
75	220-240V AC	300-1500mA	8-43	0.9

## ACCESSORIES

CCREMOTEB	Handheld remote control	Sold Separately
CCRFCONVWIFI	Colour Change RF-WIFI Wall Covertor, 12VDC	Sold Separately
CR575RGBW	5-Core PVC Cable	Sold Separately
LEDRGBWEXT	Colour Change 5-core extension lead for RGBW products	Sold Separately