

All-in-one Driver for
RGBW/RGB Systems

Selectable Voltage by dials
(8-43V)

Receives RF signal

WARRANTY

Warranty

5 years

FEATURES & BENEFITS

4 channel output Constant Current (RGBW)

Multiple control inputs

Works with 350mA to 1500mA & 8-43V products

Power repeaters (PR3011) are required for RF installations with multiple zones that want to colour cycle. Requires driver.



CCDRV75RF

75W RF Driver

INSTALLATION INFORMATION

| | |
|-----------------------------|-----------------------------|
| Input | 220-240V AC |
| Maximum Ambient Temperature | -25°C - 40°C |
| Inrush Current | COLD START Max. 2A @ 230VAC |
| UK Bathroom Zone | 2 |
| SELV | Yes |
| Electric Class (1, 2, 3) | 2 |
| Power Factor | 0.9 |

Electrical Characteristics

| Driver Rated Wattage | Driver Input Voltage | Drive Current | Driver Output Voltage | Power Factor |
|----------------------|----------------------|---------------|-----------------------|--------------|
| 75W | 220-240V AC | 300-1500mA | 8-43V | 0.9 |

ACCESSORIES

| | | |
|--------------|---|-----------------|
| CCREMOTEB | Handheld remote control | Sold Separately |
| CCRFCONVWIFI | Colour Change RF-WIFI Wall Covetor, 12VDC | Sold Separately |
| CR575RGBW | 5-Core PVC Cable | Sold Separately |
| LEDRGBWEXT | Colour Change 5-core extension lead for RGBW products | Sold Separately |