

## WARRANTY

Warranty

5 years

## FEATURES & BENEFITS

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Daylight harvesting

Default is

Options -

30Lux/50Lux/80Lux/120Lux

200Lux/250Lux/300Lux/350Lux

400Lux

When ambient brightness is lower than the preset lux level options, the luminaire dim up to maintain the desired lux level, when ambient brightness is brighter than preset lux level, the luminaire will hold off.

Alternately, press 'Scene' button on remote to Instead of giving a specific lux level

Photocell Lights will switch automatically ON when ambient brightness is lower than preset level and automatically OFF when ambient brightness is 10 times higher than preset level.

Daylight photocell

Default is

Options to have 2Lux/10Lux

# DAYLIGHT SENSOR

Daylight harvesting sensor with photocell

## FEATURES

IP rating	IP65
-----------	------

## INSTALLATION INFORMATION

Input	10.5-15V DC
Weight	0.03
UK Bathroom Zone	N/A
Install Connector Type	Zhaga Book 18

## PHOTOMETRICS @ 25°C

Product code	Finish
HBDLS	Matt black RAL9017

## ACCESSORIES

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------