



## PIR Sensor

Passive infra-red motion sensor with daylight threshold switch

### Features

|           |      |
|-----------|------|
| IP rating | IP65 |
|-----------|------|

### Installation Information

|                        |               |
|------------------------|---------------|
| Input                  | 10.5-15V DC   |
| Weight                 | 0.03          |
| UK Bathroom Zone       | N/A           |
| Install Connector Type | Zhaga Book 18 |

### Photometrics @ 25°C

| Product Code | Finish             |
|--------------|--------------------|
| HBPIR        | Matt black RAL9017 |

### Accessories

|          |                        |                 |
|----------|------------------------|-----------------|
| Area Bay | High bay product range | Sold Separately |
|----------|------------------------|-----------------|

### Guarantee

|          |         |
|----------|---------|
| Warranty | 5 years |
|----------|---------|

### Features & benefits

- Plugs into the centre of the Area Bay luminaire using the Zhaga socket
- Typical installation height 8-13m
- Hold time Default is 5 seconds - Options 30s/1min/3min/5min/10min/20min/30min
- Stand-by dimming level: Default is 10% Options - 20%/30%/50%
- Stand-by period: Default is 0 seconds - Options - 10s/30s/1min/5min/10min/30min
- Daylight threshold: Default is 'disable' - Options - 2Lux/10Lux/30Lux/50lux/120Lux/200Lux/250Lux/300Lux
- Use remote controller HBREM to commission