



Typical installation height 8-12m

Use remote controller UNREMOTEMWS to commission

PIR & DAYLIGHT SENSOR

Passive infra-red motion sensor with daylight harvesting photocell

FEATURES

IP rating	IP65
-----------	------

INSTALLATION INFORMATION

Input	10.5-15V DC
Weight	0.03
UK Bathroom Zone	N/A
Install Connector Type	Zhaga Book 18

PHOTOMETRICS @ 25°C

Product code	Finish
HBPIRDLDD	Matt black RAL9017

ACCESSORIES

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------

WARRANTY

Warranty 5 years

FEATURES & BENEFITS

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Only have the light turn on when a specific lux level is reached.

Light dims to a low level when there is inactivity

The light can adjust its brightness in response to changing natural daylight. Increased natural daylight = reduce light brightness and vice versa

Hold time Default is 5 seconds - Options 30s/1min/3min/5min/10min/20min/30min

Stand-by dimming level: Default is 10% Options - 20%/30%/50%

Stand-by period: Default is 0 seconds - Options - 10s/30s/1min/5min/10min/30min/60min/∞

Daylight threshold: Default is 'disable' - Options -

2Lux/10Lux/30Lux/50lux/120Lux/200Lux/250Lux/300Lux/350Lux/400Lux

Daylight harvesting activated when Daylight threshold is set to a lux level, standby set to ∞ and standby set to 10%/20%/30%