



collingwood



UGR19



Wattage switchable from 13W to 26W



Ultra-efficient up to 156 Lm/W

# Trinity Versa 600x600

## Features

IP rating	IP20
IK rating	IK07
CSP Switchable	Single CCT
UGR	UGR<19
Sensor Option	Plug-in PIR
Dimmable Option	Yes (DALI-2, PUSH-DIM)
LED Lifetime	L80 50,000h
Colour Rendering Index	CRI>80
Colour Consistency	SDCM4
Emergency Option	Yes, Manual, Self and DALI-2 Test

## Installation Information

Input	220-240V AC
Maximum Ambient Temperature	-20°C - 40°C
Weight	3.8kg
Insulation Coverable	No
Inrush Current	13.8A 0.16ms
Construction Material	Steel Housing, Prismatic Diffuser, TP(a) Rated
UK Bathroom Zone	N/A
SELV	Yes
Electric Class (1, 2, 3)	2
Install Connector Type	Easy-fit connector
UK Building Regulations	Part P & L
Mounting Options	Ceiling
TP rating	TP(a)

## Guarantee

Warranty	5 years
Battery Warranty	5 years
On-Site Warranty	2 years

## Features & benefits

- Suitable for classroom, office and retail applications
- Direct/Indirect design provides a soft low glare lit effect
- TP(a) rated diffuser and 850-deg glow wire test approval, makes the product to be suitable for use in fire escape routes
- Plug-in PIR accessory to keep the light OFF when no-one is present
- Energy class B rating
- DALI-2 and PUSH-DIM driver options
- Lay-in, pull-up into (up to 40mm) ceiling depths using TRIKITPULL
- Manual-test, self-test and DALI-2 test emergency options

## Photometrics @ 25°C

Product Code	Finish	Type	Beam	W	Colour	lm	lm/W	Energy
TRI66N40	White	On-Off	80°	13W	4000K	1900	146	
				16W	4000K	2500	156	
				18W	4000K	2800	156	
				20W	4000K	3100	155	
				26W	4000K	3700	142	
TRI66X40	White	Driver excluded	80°	13W	4000K	1900	146	
				16W	4000K	2500	156	
				18W	4000K	2700	156	
				20W	4000K	3100	155	
				26W	4000K	3900	142	

## Wiring Information

Cable / Flying Lead	N/A
Type of Wiring Required	Parallel

## Accessories

LEDEPI0EM	Manual-test emergency converter	Sold Separately
LEDEPI0	Manual & Self-test switchable emergency converter	Sold Separately
LEDEPI0DA	DALI-2 emergency converter (use with driver TRISDIMDRV)	Sold Separately
TRIONOFFPIR	PIR on-off sensor including Easy-Fit Connector	Sold Separately
TRISDIMPIR	Step-dim sensor (requires TRISDIMDRV)	Sold Separately
TRIDALIPIR	DALI 2 PIR Sensor (Requires TRIDALIDRV)	Sold Separately
TRIREMOTE	Remote controller for programming TRIONOFFPIR & TRISDIMPIR	Sold Separately

## Beam angle: 80°

