



## Mains Low Voltage Ceiling Downlight Converter


Mains or low voltage converter with GU10 and GU5.3 lamp holders polished chrome

### DESCRIPTION

Converts traditional mains R50, R64 and R80 downlight and eyeball dimensions to modern GU10 or low voltage lighting: allows use of modern light source without expensive repairs & decoration

### FEATURES

- Pre-wired with ceramic GU5.3 low voltage lampholder, ceramic GU10 mains lampholder option also included
- Fitting is rated at 50W max
- Converts traditional mains R50, R64 and R80 downlights to GU10 or LV lighting
- Hole cut out 70-140mm - replaces a wide range of outdated downlights
- Shallow profile, neat, unobtrusive solution



### GENERAL INFORMATION

<b>Colour / Finish</b>	Polished chrome effect	<b>Application</b>	Internal
<b>Mounting Type</b>	Recessed	<b>Product Warranty</b>	1 Year
<b>Net Weight</b>	0.3 kg		

### TECHNICAL INFORMATION

<b>Frequency</b>	50Hz	<b>Construction Materials Line 1</b>	Steel
<b>Dimensions - Height</b>	125 mm	<b>Dimensions - Width</b>	150 mm
<b>Dimensions - Depth</b>	150 mm	<b>IP Rating</b>	IP20





IP20

## PACKAGING

<b>Packaging Type</b>	Plastic Blister
<b>Individual unit gross weight</b>	254 g
<b>Intermediate Carton Depth (mm)</b>	175 mm
<b>Intermediate Carton Width (mm)</b>	295 mm
<b>Intermediate Carton Height (mm)</b>	175 mm
<b>Intermediate Pack Qty.</b>	5
<b>Pallet Layer Qty</b>	200
<b>Pallet Layers</b>	3
<b>Pallet Qty</b>	600
<b>MOM / OPQ</b>	1 / 40

