
# 1.85mm Male to 1.85mm Female Adapter with Right Angle, DC - 67GHz FR1-1.85-JWKS





Dimensions are in mm

# Product Configuration

Connector 1 Series 1.85mm Connector 1 Polarity Standard Connector 1 Gender Male Connector 1 Impedance (Ohm) 50 Connector 1 Mount Method None Connector 2 Series 1.85mm Connector 2 Polarity Standard Connector 2 Gender Female Connector 2 Impedance (Ohm) 50 Connector 2 Mount Method None Body Style Right Angle

#### **Mechanical Data**

Connector 1 Body Material Stainless Steel Connector 1 Body Plating **Passivated** Connector 2 Body Material Stainless Steel Connector 2 Body Plating Passivated Min. Mating Cycles ≥500 Weight 7.17 g

## **Electrical Specifications**

DC-67GHz Frequency **VSWR** 1.25

Insertion Loss ≤0.08 xSqt.(f\_GHz)

## **Enviromental Specifications**

**RoHS** Compliant Yes

Operating Temperature -55 °C to +165 °C

Range

MIL/STD N/A