Datasheet

2.92mm Male Right Angle RF Connector for 0.086" Coax Cable | Solder Attachment | 2.92-JWB2-1 DC–40GHz



Product Configuration

Connector Series	2.92mm
Connector Polarity	Standard
Connector Gender	Male
Body Style	Right Angle
Termination Type	Coax
Connector Impedance (Ohm)	50

Mechanical Data

Min. Mating Cycles	≥500
Body Material	Stainless Steel
Body Plating	Passivated

Electrical Specifications

Frequency	DC - 40GHz
VSWR / Return Loss	1.35
Insertion Loss	≤ 0.05 x Sqrt.(f_GHz)

Enviromental Specifications

RoHS Compliant	Yes
Operating Temperature Range	-55°C to +165°C

Gwave Technology Inc
(888)251-2240
87 Patricia Ct, Mountain View, CA 94041
sales@gwavetech.com
www.gwavetech.com