

BMA Male Connector for RG405 or .086" Cable, 4 Holes Flange, DC-18GHz

P/N: FR2-JBMA-JFB2



Product Configuration

Body Style	Straight
Connector Series	BMA
Connector Polarity	Standard
Connector Gender	Male
Termination Type	Coax
Connector Impedance (Ohm)	50
Mount Method	4 Hole Flange

Electrical Specifications

Frequency	DC to 18GHz
VSWR	1.30 to 18GHz
Insertion Loss	$\leq 0.10 \times \text{Sqrt.}(f_GHz)$

Mechanical Data

Min. Mating Cycles	≥ 500
Body Material	Brass
Body Plating	Gold

Environmental Specifications

RoHS Compliant	Yes
Operating Temperature Range	-55 °C to +165 °C
MIL/STD	N/A