Flexi RF
Reliable RF Components In Stock

Datasheet

TNC Male Connector for .141"Series Cables | DC - 18GHz

P/N: FR2-TNC-JB3



Product Configuration

Body Style	Straight
Connector Series	TNC
Connector Polarity	Standard
Connector Gender	Male
Termination Type	Coax
Connector Impedance (Ohm)	50
Mount Method	None

Electrical Specifications

Frequency	DC - 18GHz
VSWR / Return Loss	1.3 to 18GHz
Insertion Loss	≤ 0.05 x Sqrt.(f_GHz)
RF Leakage	90dB

Mechanical Data

Min. Mating Cycles	≥500
Body Material	Beryllium Copper
Body Plating	Passivated

Enviromental Specifications

RoHS Compliant	Yes
Operating Temperature Range	-55 ºC to +165ºC
MIL/STD	N/A

Flexi RF Inc
(650)880-9199
20195 Stevens Creek Blvd, Suite 220, Cupertino, CA 95014
sales@flexirf.com
www.flexirf.com