

**EU 1G DIMMER /  
250W MULTIPOINT  
LED / RETRACTIVE**

**ACTION: DIMMER SWITCH**

**KNURL: CROSS**

**RANGE: DIMMER SWITCHES**

A solid metal dimmer switch with our classic diamond-cut knurling. The switch is finished with a solid metal plate and our signature coin screws. Available in five different finishes, they can be used in combination with our matching toggle switches, sockets and USB outlets.



---

**SPECIFICATIONS**

---

Solid metal switch plate with one multipoint dimmer, in our signature white, steel, brass, smoked bronze and black finishes.

Module: CDM-142038  
Style: Push On / Off Rotary Dimmer  
Switching: Multi-location dimming using retractive switches  
Input: 240VAC  
Dimming Type: Auto-detect trailing edge and leading edge (with manual override)  
Load: 10-350W - Incandescent / 3-250W - LED  
Certified for use in UK, Europe and Russia: UKCA / CE / EAC  
Certification: EN 60669-2-1

For use with retractive switches on retractive dimming circuits, to control dimming from multiple locations.  
Not compatible with standard wiring and standard 1-way, 2-way and 3-way wiring accessories.  
Not suitable for motors, fans or any other type of large inductive load.

The dimmer switch incorporates a soft-start feature, which may result in a 1–2 second delay before full illumination to reduce inrush current and extend lamp life.  
This module is custom to Buster + Punch and works only with our Cross and Linear knurled dimmer knobs.  
note: rotary action includes a soft, audible ticking feedback during adjustment.

Compatible with European standard electricity backboxes. Backbox must be flush mounted.  
For indoor use only.  
This piece features a 6.5mm shadow gap when installed.

---

**FINISH & SKU NUMBERS**

---

sku:	finish:	size:
CDR-021975	● black	1G
CDR-051976	● brass	1G
CDR-091978	● smoked bronze	1G
CDR-141974	● white	1G

---

**INCLUDED**

---

1 x Complete Dimmer Switch Assembly

---

**PLEASE NOTE**

---

DISCLAIMER: Always consult a trade professional when installing this product. Buster + Punch is not responsible for the usage or feasibility of installation requirements. This product is not suitable for damp or wet environments.

---

**CARE INSTRUCTIONS**

---

Wipe with a dry lint free cloth with no loose hairs, avoid using any chemicals. Please note that finishes may age naturally with time and regular use.