

## BUSTER BULB / B22

The World's first designer LED bulb. This bulb has a life span of 30,000 hours. Available in Gold or Smoked finish. The resin light pipe at the centre of the bulb is where all the magic happens, allowing the bulb to create a subtle ambient light whilst at the same time throw focused spot light onto tables & surfaces below.

B+P light fittings are typically not designed for B22 lamp caps, but we understand you may wish to give your other B22 light fittings the B+P aesthetic. Our advice is always to check lamp cap compatibility before purchase!




SPECIFICATIONS

5W Dimmable LED Buster Bulb  
Screw fitting: B22  
Supply: 220-240 VAC  
Expected Life: 30,000 hrs  
Lumen: Gold max 200, Smoked max 130  
Light appearance: Gold 2500K, Smoked 2600K  
CRI: 80  
Power factor: 0.8  
CE certified.\*  
For indoor use only.  
\*Official data doc can be supplied upon request.

2W Non-Dimmable LED  
Screw fitting: B22  
Supply: 100-240 VAC  
Expected Life: 30,000 hrs  
Lumen: Gold max 100, Smoked max 75  
Light appearance: Gold 2500K, Smoked 2600K  
CRI: 80  
Power factor: 0.5  
CE certified.\*  
For indoor use only.  
\*Official data doc can be supplied upon request.

FINISH & SKU NUMBERS

sku:	finish:	size:
BB-TD-B22-D-GO-B	 gold	Dimmable (5W)
BB-TD-B22-D-SM-B	 smoked	Dimmable (5W)
BB-TD-B22-ND-GO-B	 gold	Non-dimmable (2W)
BB-TD-B22-ND-SM-B	 smoked	Non-dimmable (2W)

CARE INSTRUCTIONS

Wipe with dry cloth with no loose hairs, avoid using any chemicals. Please note all finishes are prone to aging.

INCLUDED

1 x Buster Bulb

PLEASE NOTE

The dimmable LED BUSTER BULB requires a LED-compatible dimmer switch, like the Buster + Punch Premium dimmer switch. They can also be used with on/off switches.

The non-dimmable LED BULB is only compatible with on/off switches.

If you are planning to use this product in conjunction with a smart or home automation system, please refer to the system manufacturers guidance to check compatibility. Our bulbs are mains operated at 240VAC. To avoid disappointment, please ensure a compatible smart module is fitted before purchase. \*

This product is specifically designed and developed for domestic use in normal conditions and operation only. The lifetime mentioned on the packaging is an average only.