

## LIGHTING INNOVATION

Casambi Logo

Wireless Logo

Energy Savings Logo

## WARRANTY

Warrant

5 vec

## FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

eliminating the need for a single router setup

Simplified Installation - No extra control wiring gateways, or routers needed

settings via the Casambi App

10-16m cone detection pattern when installed at 7m

# CASAMBI WIRELESS BOLT-ON SENSOR

PIR+Daylight M20 Conduit Entry Sensor for use up to 7m

#### **FEATURES**

IP rating IP65
Dimmable Option Yes (0-10V)

## INSTALLATION INFORMATION

Input 220-240V AC

Maximum Ambient Temperature -20°C - 60°C

Electric Class (1, 2, 3) 2

Install Connector Type Flying lead

UK Building Regulations Part P & L

Dimmer Type App controlled

## PHOTOMETRICS @ 25°C

Product code	Finish
CASBOLT7W	White

## **ACCESSORIES**

Use with Borealis Versa	Requires 0-10V driver	Sold Separately
Use with Caiman Versa	Requires 0-10V driver	Sold Separately
Use with Uniform Versa	Requires 0-10V driver	Sold Separately
Use with Rack Bay	Requires 0-10V driver	Sold Separately