



Casambi Ready



Bluetooth Mesh



Wireless Control

WARRANTY

Warranty

5 years

FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation – No extra control wiring, gateways, or routers needed

Fast Commissioning – Configure and adjust settings via the Casambi App

10-16m cone detection pattern when installed at 7m



CASAMBI WIRELESS BOLT-ON SENSOR

PIR+Daylight M20 Conduit Entry Sensor for use up to 7m

FEATURES

IP rating	IP65
Dimmable Option	Yes (0-10V)

INSTALLATION INFORMATION

Input	220-240V AC
Maximum Ambient Temperature	-20°C - 60°C
Electric Class (1, 2, 3)	II
Install Connector Type	Flying lead
UK Building Regulations	Part P & L
Dimmer Type	App controlled

PHOTOMETRICS @ 25°C

Product code	Finish
CASBOLT7W	White

ACCESSORIES

Use with Borealis Versa	Requires 0-10V driver	Sold Separately
Use with Caiman Versa	Requires 0-10V driver	Sold Separately
Use with Uniform Versa	Requires 0-10V driver	Sold Separately
Use with Rack Bay	Requires 0-10V driver	Sold Separately

