

LIGHTING INNOVATION

Casambi Logo

Wireless Logo

Energy Savings Logo

WARRANTY

Warranty

5 vea

FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation – No extra control wiring gateways, or routers needed

settings via the Casambi App

Input Power 5-12W, Output Voltage Range
DC28-40V

Rated Output Current 75-250mA adjustable by DIP

CASAMBI WIRELESS 10W DRIVER

Pre-wired with DC jack for plug-in to Panels & Downlights

FEATURES

IP rating IP20
Dimmable Option Yes

INSTALLATION INFORMATION

PHOTOMETRICS @ 25°C

Product code	Finish
CASDRVIOW	White

ACCESSORIES

Use with Thea Pro 10W	Plug-in to driverless product	Sold Separately
Use with Thea Lite 10W	Plug-in to driverless product	Sold Separately