



Casambi Ready



Bluetooth Mesh



Wireless Control

WARRANTY

Warranty

5 years

FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation – No extra control wiring, gateways, or routers needed

Fast Commissioning – Configure and adjust settings via the Casambi App

Input Power 5-12W, Output Voltage Range DC28-40V

Rated Output Current 75-250mA adjustable by DIP



CASAMBI WIRELESS 10W DRIVER

Pre-wired with DC jack for plug-in to Panels & Downlights

FEATURES

IP rating	IP20
Dimmable Option	Yes

INSTALLATION INFORMATION

Input	220-240V AC
Maximum Ambient Temperature	-20°C - 50°C
Electric Class (1, 2, 3)	II
Install Connector Type	Push-fit terminals 0.75 - 2.5mm ²
UK Building Regulations	Part P & L
Dimmer Type	App controlled

PHOTOMETRICS @ 25°C

Product code	Finish
CASDRV10W	White

ACCESSORIES

Use with Thea Pro 10W	Plug-in to driverless product	Sold Separately
Use with Thea Lite 10W	Plug-in to driverless product	Sold Separately

