



Casambi Ready



Bluetooth Mesh



Wireless Control

WARRANTY

Warranty

5 years

FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation – No extra control wiring, gateways, or routers needed

Fast Commissioning – Configure and adjust settings via the Casambi App

Input Power 14-25W, Output Voltage Range DC28-40V

Rated Output Current 250-600mA adjustable by DIP



CASAMBI WIRELESS 25W DRIVER

Pre-wired with DC jack for plug-in to Panels & Downlights

FEATURES

IP rating	IP20
Dimmable Option	Yes

INSTALLATION INFORMATION

Input	220-240V AC
Maximum Ambient Temperature	-20°C - 50°C
Electric Class (1, 2, 3)	II
Install Connector Type	Push-fit terminals 0.75 - 2.5mm ²
UK Building Regulations	Part P & L
Dimmer Type	App controlled

PHOTOMETRICS @ 25°C

Product code	Finish
CASDRV25W	White

ACCESSORIES

Use with Trinity Versa 13-20W	Plug-in to driverless product	Sold Separately
Use with Solis Pro 22W	Plug-in to driverless product	Sold Separately
Use with Thea Pro 14-25W	Plug-in to driverless product	Sold Separately
Use with Thea Lite 14-25W	Plug-in to driverless product	Sold Separately

