

CASAMBI WIRELESS 25W DRIVER

Pre-wired with DC jack for plug-in to Panels & Downlights

FEATURES

IP rating	IP20
Dimmable Option	Yes

INSTALLATION INFORMATION

Input	220-240V AC	
Maximum Ambient Temperature	-20°C - 50°C	
Weight	0.097kg	
Electric Class (1, 2, 3)	II	
Install Comments Tons	Push-fit terminals 0.75 -	
Install Connector Type	2.5mm ²	
UK Building Regulations	Part P & L	
Dimmer Type	App controlled	

PHOTOMETRICS @ 25°C

Product code	Finish
CASDRV25W	White

ACCESSORIES

	Use with Trinity Versa 13-20W	Plug-in to driverless product	Sold Separately
	Use with Solis Pro 22W	Plug-in to driverless product	Sold Separately
	Use with Thea Pro 14-25W	Plug-in to driverless product	Sold Separately
	Use with Thea Lite 14-25W	Plug-in to driverless product	Sold Separately



LIGHTING INNOVATION



Casambi Ready



Bluetooth Mesh



Wireless Control

WARRANTY

Marrant

5 years

FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation – No extra control wiring gateways, or routers needed

Fast Commissioning – Configure and adjus settings via the Casambi App

Input Power 14-25W, Output Voltage Range DC28-40V

Rated Output Current 250-600mA adjustable b
DIP

