

Casambi Logo

Wireless Logo

Energy Savings Logo

WARRANTY

Warranty

5 years

FEATURES & BENEFITS

Casambi's Bluetooth Low Energy (BLE) system eliminates the need for control wiring, allowing for quick and easy installation in any project.

All nodes are connected to one another, eliminating the need for a single router setup

Simplified Installation - No extra control wiring, gateways, or routers needed

Fast Commissioning - Configure and adjust settings via the Casambi App

Use with CASZHAGAMB to create a wireless control line

CASAMBI WIRELESS ZHAGA NODE

Wireless Node for use with Area Bay up to 12m

FEATURES

IP rating	IP65
Dimmable Option	Yes (0-10V)

INSTALLATION INFORMATION

Input	220-240V AC
Maximum Ambient Temperature	-20°C - 60°C
Electric Class (1, 2, 3)	3
Install Connector Type	Zhaga Book 18
UK Building Regulations	Part P & L
Dimmer Type	App controlled

PHOTOMETRICS @ 25°C

Product code	Finish
CASZHAGASB	Black

ACCESSORIES

Use with Area Bay	Requires 0-10V driver	Sold Separately
--------------------------	-----------------------	-----------------