



## MICROWAVE SENSOR

Motion sensor with daylight threshold switch

### FEATURES

<b>IP rating</b>	IP65
------------------	------

### INSTALLATION INFORMATION

<b>Input</b>	10.5-15V DC
<b>Weight</b>	0.03
<b>UK Bathroom Zone</b>	N/A
<b>Install Connector Type</b>	Zhaga Book 18

### PHOTOMETRICS @ 25°C

<b>Product code</b>	<b>Finish</b>
<b>HBMWS</b>	Matt black RAL9017

### ACCESSORIES

<b>Area Bay</b>	High bay product range	Sold Separately
-----------------	------------------------	-----------------

### WARRANTY

Warranty	5 years
----------	---------

### FEATURES & BENEFITS

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Typical installation height 8-13m

Hold time

Default is 5 seconds

Options -

30s/1min/3min/5min/10min/20min/30min

Stand-by dimming level

Default is 10%

Options - 20%/30%/50%

Stand-by period

Default is 0 seconds

Options - 10s/30s/1min/5min/10min/30min

Daylight threshold

Default is 'disable'

Options -

2Lux/10Lux/30Lux/50Lux

120Lux/200Lux/250Lux

300Lux/350Lux/400Lux