

# MICROWAVE SENSOR

Motion sensor with daylight threshold switch

INSTALLATION	ON INFORMATION
Input	10.5-15V DC
Weight	0.03
UK Bathroom Zone	N/A
Install Connector Type	Zhaga Book 18
	Input Weight UK Bathroom Zone

## PHOTOMETRICS @ 25°C

Product code	Finish
HBMWS	Matt black RAL9017

## **ACCESSORIES**

Area Bay High bay product range	Sold Separately
---------------------------------	-----------------



LIGHTING INNOVATION

## WARRANTY

Warranty

5 years

## FEATURES & BENEFITS

Plugs into the centre of the Area Bay luminaire using the Zhaga socket

Typical installation height 8-13m

Hold tim

Default is 5 second

Options

30s/Imin/3min/5min/10min/20min/30mii

Stand-by dimming level

Default is 10%

Options - 20%/30%/50%

Stand-by period

Default is 0 seconds

Options - 10s/30s/Imin/5min/10min/30min

Daylight threshold

Default is 'disable'

Option

2Lux/10Lux/30Lux/50lux

300Lux/350Lux/400Lux