



## PIR Sensor

Passive infra-red motion sensor with daylight threshold switch

### Features

IP rating	IP65
-----------	------

### Installation Information

Input	10.5-15V DC
Weight	0.03
UK Bathroom Zone	N/A
Install Connector Type	Zhaga Book 18

### Photometrics @ 25°C

Product Code	Finish
HBPIR	Matt black RAL9017

### Accessories

Area Bay	High bay product range	Sold Separately
----------	------------------------	-----------------

### Guarantee

Warranty	5 years
----------	---------

### Features & benefits

- Plugs into the centre of the Area Bay luminaire using the Zhaga socket
- Typical installation height 8-13m
- Hold time Default is 5 seconds - Options 30s/1min/3min/5min/10min/20min/30min
- Stand-by dimming level: Default is 10% Options - 20%/30%/50%
- Stand-by period: Default is 0 seconds - Options - 10s/30s/1min/5min/10min/30min
- Daylight threshold: Default is 'disable' - Options - 2Lux/10Lux/30Lux/50lux/20Lux/200Lux/250Lux/300Lux
- Use remote controller HBREM to commission